

C Operator Precedence

The following table lists the precedence and associativity of C operators. Operators are listed top to bottom, in descending precedence.

Precedence	Operator	Description	Associativity
1	++ --	Suffix/postfix increment and decrement	Left-to-right
	()	Function call	
	[]	Array subscripting	
	.	Structure and union member access	
	-> (<i>type</i>){ <i>list</i> }	Structure and union member access through pointer Compound literal(C99)	
2	++ --	Prefix increment and decrement	Right-to-left
	+ -	Unary plus and minus	
	! ~	Logical NOT and bitwise NOT	
	(<i>type</i>)	Type cast	
	*	Indirection (dereference)	
	&	Address-of	
	sizeof _Alignof	Size-of ^[note 1] Alignment requirement(C11)	
3	* / %	Multiplication, division, and remainder	Left-to-right
4	+ -	Addition and subtraction	
5	<< >>	Bitwise left shift and right shift	
6	< <=	For relational operators < and ≤ respectively	
	> >=	For relational operators > and ≥ respectively	
7	== !=	For relational = and ≠ respectively	
8	&	Bitwise AND	
9	^	Bitwise XOR (exclusive or)	
10		Bitwise OR (inclusive or)	
11	&&	Logical AND	
12		Logical OR	
13 ^[note 2]	? :	Ternary conditional ^[note 3]	
14	=	Simple assignment	Right-to-left
	+= -=	Assignment by sum and difference	
	*= /= %=	Assignment by product, quotient, and remainder	
	<<= >>=	Assignment by bitwise left shift and right shift	
	&= ^= =	Assignment by bitwise AND, XOR, and OR	
15	,	Comma	Left-to-right

ASCII Table

Dec = Decimal Value

Char = Character

'5' has the int value 53

if we write '5'-'0' it evaluates to 53-48, or the int 5

if we write char c = 'B'+32; then c stores 'b'

Dec	Char	Dec	Char	Dec	Char	Dec	Char
0	NUL (null)	32	SPACE	64	@	96	`
1	SOH (start of heading)	33	!	65	A	97	a
2	STX (start of text)	34	"	66	B	98	b
3	ETX (end of text)	35	#	67	C	99	c
4	EOT (end of transmission)	36	\$	68	D	100	d
5	ENQ (enquiry)	37	%	69	E	101	e
6	ACK (acknowledge)	38	&	70	F	102	f
7	BEL (bell)	39	'	71	G	103	g
8	BS (backspace)	40	(72	H	104	h
9	TAB (horizontal tab)	41)	73	I	105	i
10	LF (NL line feed, new line)	42	*	74	J	106	j
11	VT (vertical tab)	43	+	75	K	107	k
12	FF (NP form feed, new page)	44	,	76	L	108	l
13	CR (carriage return)	45	-	77	M	109	m
14	SO (shift out)	46	.	78	N	110	n
15	SI (shift in)	47	/	79	O	111	o
16	DLE (data link escape)	48	0	80	P	112	p
17	DC1 (device control 1)	49	1	81	Q	113	q
18	DC2 (device control 2)	50	2	82	R	114	r
19	DC3 (device control 3)	51	3	83	S	115	s
20	DC4 (device control 4)	52	4	84	T	116	t
21	NAK (negative acknowledge)	53	5	85	U	117	u
22	SYN (synchronous idle)	54	6	86	V	118	v
23	ETB (end of trans. block)	55	7	87	W	119	w
24	CAN (cancel)	56	8	88	X	120	x
25	EM (end of medium)	57	9	89	Y	121	y
26	SUB (substitute)	58	:	90	Z	122	z
27	ESC (escape)	59	;	91	[123	{
28	FS (file separator)	60	<	92	\	124	
29	GS (group separator)	61	=	93]	125	}
30	RS (record separator)	62	>	94	^	126	~
31	US (unit separator)	63	?	95	_	127	DEL